

Ludwig-Thoma-Haus DMX Patch

	Fix ID	Name	Position	Modus	Anz. Kanäle	Adresse
6x	1	Prolights - Eclipse HD2	Front		1	1.001
	2	Prolights - Eclipse HD2	Front		1	1.002
	3	Prolights - Eclipse HD2	Saal links		1	1.003
	4	Prolights - Eclipse HD2	Saal links		1	1.004
	5	Prolights - Eclipse HD2	Saal rechts		1	1.005
	6	Prolights - Eclipse HD2	Saal rechts		1	1.006
4x	7	Prolights - Eclipse HDTWC	Gasse SR		12	1.007
	8	Prolights - Eclipse HDTWC	Gasse SR		12	1.019
	9	Prolights - Eclipse HDTWC	Gasse SL		12	1.031
	10	Prolights - Eclipse HDTWC	Gasse SL		12	1.043
10x	11	Prolights - Eclipsefresnel TW	Portal		12	1.055
	12	Prolights - Eclipsefresnel TW	Portal		12	1.067
	13	Prolights - Eclipsefresnel TW	Portal		12	1.079
	14	Prolights - Eclipsefresnel TW	Portal		12	1.091
	15	Prolights - Eclipsefresnel TW	Gasse SR		12	1.103
	16	Prolights - Eclipsefresnel TW	Gasse SR		12	1.115
	17	Prolights - Eclipsefresnel TW	Gasse SL		12	1.127
	18	Prolights - Eclipsefresnel TW	Gasse SL		12	1.139
	19	Prolights - Eclipsefresnel TW	Front		12	1.151
	20	Prolights - Eclipsefresnel TW	Front		12	1.163
9x	21	Feiner - LE.FL1200.DMX	Zug 3	1 Kanal	1	1.175
	22	Feiner - LE.FL1200.DMX	Zug 3	1 Kanal	1	1.176
	23	Feiner - LE.FL1200.DMX	Zug 3	1 Kanal	1	1.177
	24	Feiner - LE.FL1200.DMX	Zug 3	1 Kanal	1	1.178
	25	Feiner - LE.FL1200.DMX	Zug 3	1 Kanal	1	1.179
	26	Feiner - LE.FL1200.DMX	Front	1 Kanal	1	1.180
	27	Feiner - LE.FL1200.DMX	Front	1 Kanal	1	1.181
	28	Feiner - LE.FL1200.DMX	Front	1 Kanal	1	1.182
	29	Feiner - LE.FL1200.DMX	Front	1 Kanal	1	1.183

Fix ID	Name	Position	Modus	Anz. Kanäle	Adresse	
8x	101	Prolights - Diamond 19cc	Zug 3	Basic 16	16	1.184
	102	Prolights - Diamond 19cc	Zug 3	Basic 16	16	1.200
	103	Prolights - Diamond 19cc	Zug 3	Basic 16	16	1.216
	104	Prolights - Diamond 19cc	Zug 3	Basic 16	16	1.232
	105	Prolights - Diamond 19cc	Zug 4	Basic 16	16	1.248
	106	Prolights - Diamond 19cc	Zug 4	Basic 16	16	1.264
	107	Prolights - Diamond 19cc	Zug 4	Basic 16	16	1.280
	108	Prolights - Diamond 19cc	Zug 4	Basic 16	16	1.296
4x	201	Chroma-Q Studioforce II 48	Portal	RGBW	5	1.312
	202	Chroma-Q Studioforce II 48	Portal	RGBW	5	1.317
	203	Chroma-Q Studioforce II 48	Portal	RGBW	5	1.322
	204	Chroma-Q Studioforce II 48	Portal	RGBW	5	1.327
6x	301	JB Lighting - P8	Saal	Mode 1	27	2.001
	302	JB Lighting - P8	Saal	Mode 1	27	2.028
	303	JB Lighting - P8	Saal	Mode 1	27	2.055
	304	JB Lighting - P8	Saal	Mode 1	27	2.082
	305	JB Lighting - P8	Saal	Mode 1	27	2.109
	306	JB Lighting - P8	Saal	Mode 1	27	2.136

Kanalbelegungen

	HDTWC 12-Kanal	Eclipsefresnel TW 12-Kanal	Diamond 19cc Basic16	Studioforce - RGBW	JB P8 - Mode 1
1	Dimmer	Dimmer	Pan	Rot	Pan
2	Shutter	Shutter	Pan fein	Grün	Pan fein
3	Rot	Rot	Tilt	Blau	Tilt
4	Orange	Orange	Tilt fein	Weiß	Tilt fein
5	Grün	Grün	Pan/Tilt Geschw.		Steuerkanal
6	Blau	Blau	Shutter		Shutter
7	Hellblau	Hellblau	Dimmer		Dimmer
8	Limette	Limette	V. Farb Funktion		Iris
9	CTO	CTO	V. Farbrad 1		Focus
10	HUE	HUE	V. Farbrad 2		Gobo 1
11	Farb Macro	Farb Macro	Rot		Gobo 1 Rotation
12	Dimmer Modus	Dimmer Modus	Grün		Gobo 2
13			Blau		Gobo 2 Rotation
14			Weiß		
15			Zoom		nächste Spalte -->
16			Control		
					...
					14 Prisma
					15 Prisma Rotation
					16 CTC 3200K
					17 Farbrademulation
					18 Pan/Tilt Geschw.
					19 Effekt Geschw.
					20 Blackout Move
					21 Animationsrad
					22 Anim. Rotation
					23 Frost
					24 Zoom
					25 Rot
					26 Grün
					27 Blau